MC 521 YELLOW LABEL SETUP FOR DUAL FULL POWER

Power **ON**
Turn Mode selector switch to **CLOSED** or **OFF**

*****Remember when releasing enter you only have 2 seconds to make a change*****

A) Hold enter and press down to #**99**
Release enter, press down one time to #**00**
B) Hold enter and press down to #**96**
Release enter, press up one time to #**01**
You will then see "A0" on display
C) Hold enter and press up to #**00**
Release enter, press up to until you see #**06**
You will then see "AO" on display
D) Hold enter and press up to #**01** (motor 01)
Release enter, go to "**00**" for right hand or "**01**" for left hand
You will then see "A0" on display
E) Hold enter and press up to #**02** (motor 02)
Release enter, go to "**00**" for right hand or "**01**" for left hand
You will then see "A)" on display
F) Hold enter and press up to #**03**
Release enter, press **UP** one time
You will see "20" briefly, then "A1" on display
G) Hold enter and press up to #**11**
As long as you don't have sentrex, release enter and change it to #**00**
You will see "A1" on display

H) With the doors in the **fully closed position**, you will now flip your mode switch to **HOLD OPEN. AS SOON AS THE DOOR BEGINS TO MOVE, FLIP THE MODE SWITCH BACK TO CLOSED/OFF**. The door will now go thru a "learn" process. This consists of the door opening and closing several times until you see "A2" on the display. Once "A2" is present you will:

I) Hold enter and press down to #**99**
Release enter, press up one time to "**01**"
It will then read "20" briefly, then go to "**00**"

At this point you may put your switch to **AUTOMATIC** and run your door.

Need additional help? Contact us at 1-800-222-9601 for Tech Support!